TS128MJF2A

128MB USB2.0 JetFlash™2A

Description

TS128MJF2A is a 128MB USB Flash Drive with 1 pcs of 128Mx8 Flash Memory assembled on printed circuit board.

Outline



Features

- Color: Silver
- USB Interface: Compliant with USB specification 2.0.
- Security Function: Password protection provided
- Boot-Up Function: Support USB-ZIP/USB-HDD boot-up mode supported
- PC-Lock Function: Makes JF2A the key to your computer
- No external power or battery needed
- LED indicates the usage status.

Dimensions

Side	Millimeters	Inches
A	75 ± 1.00	2.95 ± 0.04
B	11 ± 1.00	0.43 ± 0.04
C	25 ± 1.00	0.98 ± 0.04

Block Diagram

- **With 1 pcs of 128Mx8 Flash Memory**



Pinouts

Pin No.	Pin Name
01	VCC
02	USB-
03	USB+
04	VSS

Pin Identification

Symbol	Function
USB-	USB differential signal:
USB+	The pairs are used to transmit Data/Address/Command
VSS	Ground
VCC	USB power input

Specifications

Storage Capacity	128MB
Data Retention	10 years
Erase Cycles	>100,000 times
Connector Durability	10,000 times
System Performance	Read: 12MB/sec (max.), Write: 8MB/sec (max.)
Power Supply	DC 5V±10% via the USB port
Temperature Range	Operation: 0-70°C, Non-Operating: -40°C-85°C
Certificates	CE, FCC, BSMI

Absolute Maximum Ratings

Symbol	Parameter	Rating	Unit
V_{CC}	Power Supply	4.5 to 5.5	V
V_{IN}	Input Voltage	3 to 3.6	V

DC Characteristics:

Symbol	Parameter	Min.	Typ.	Max.	Units
I_{IL}	Input Leakage Current (No pull-up or pull-down)	-10		10	μA
I_{OZ}	Tri-State Leakage Current	-10		10	μA
V_{IL}	Input Low Voltage			0.8	V
V_{IH}	Input High Voltage	2.0			V
V_{OL}	Output Low Voltage (I_{OL}=4mA)			0.4	V
V_{OH}	Output High Voltage (I_{OH}=4mA)	2.4			V
Rt	Input pull-up/down resistance (V_{IL}=0V or V_{IH}= V_{CC})	40	75	190	KΩ
I_{ACT}	Active Current			73	mA
I_{SLP}	Sleep Current			120	μA

Recommended Operating Conditions

Symbol	Parameter	Min.	Typ.	Max.	Units
V_{CC}	Power Supply Voltage	4.5	5	5.5	V
V_{IN}	Input Voltage	3	3.3	3.6	V
V_{CC18}	Internal Power Supply	1.62	1.8	1.98	V

Above technical information is based on industry standard data and tested to be reliable. However, Transcend makes no warranty, either expressed or implied, as to its accuracy and assumes no liability in connection with the use of this product. Transcend reserves the right to make changes in specifications at any time without prior notice.